

# EasyLogic™ MP-C-M

## Controller Models

Part numbers: SXW MPC24AM10001 and SXW MPC36AM10001

### Safety Information


Electrical equipment should be installed, operated, serviced, and maintained only by qualified personnel. No responsibility is assumed by Schneider Electric for any consequences arising out of the use of this material. Carefully read these instructions and all information relevant for this product before trying to install it. See the list of technical literature.

### Technical Literature

- SpaceLogic and EasyLogic - Hardware Reference Guide, 04-XX001-XX-en


The technical literature and declarations of conformity can be accessed on the Schneider Electric extranet, [ecoxpert.se.com](http://ecoxpert.se.com). Contact your local Schneider Electric sales office for a hard copy of the documentation or for additional information.

### Dimensions



### Installation Orientations

Normal operation, 0 to 50 °C (32 to 122 °F):




### Installing the Device on a DIN Rail

#### NOTICE


##### CONTROLLER DAMAGE

Use the DIN rail end clip when you install the controller on a vertical DIN rail.

Failure to follow these instructions can result in equipment damage.



## Installing the Device on a Wall



## Connections and DIP Switch

### ⚠️ DANGER

#### HAZARD OF ELECTRIC SHOCK, EXPLOSION, OR ARC FLASH

- Disconnect all line voltage connected to the controller and its relay outputs before working on the device.
- More than one disconnect switch may be required to de-energize this equipment before servicing.
- Connect only devices with safe extra low voltage equipment (SELV/PELV) inputs/outputs to the controller universal inputs/outputs.


Failure to follow these instructions will result in death or serious injury.

### NOTICE

#### CONTROLLER DAMAGE

Before powering up MP-C, ensure that the input power polarity is correct and that the voltage level meets the specifications of the controller.


Failure to follow these instructions can result in equipment damage.





- A** Fixed screw terminal blocks (upper) for power and I/O
- B** Fixed screw terminal blocks (lower) for I/O
- C** Address DIP switch
- D** Removable screw terminal block for RS-485

## Connections and DIP Switch, continued





Torque: 0.56 to 0.79 Nm (5 to 7 lbf.in)



### MP-C-24A-M



### MP-C-36A-M



NOTE: Configure a unique MS/TP address during installation. Position 8 is not used.

More info See Hardware Ref. Guide

## Configuring a Unique MS/TP Address

Configure a unique MS/TP address for the device during installation. Use position 1 to 7 on the Address DIP switch. Position 1 to 7 represent the binary values 1, 2, 4, 8, 16, 32, and 64. For example, to configure MS/TP address 6, set DIP switches 2 and 3 to ON and switches 1, 4, 5, 6, and 7 to OFF. For more information, see the SpaceLogic and EasyLogic - Hardware Reference Guide.

## Wiring

Recommended screw tightening torque for removable screw terminal block: 0.56 to 0.79 Nm (5 to 7 lbf.in)  
 Recommended screw tightening torque for fixed screw terminal blocks: 0.56 to 0.79 Nm (5 to 7 lbf.in)  
 For information on wiring, see the SpaceLogic and EasyLogic - Hardware Reference Guide.

## Part Numbers

Product	Part number
MP-C-24A-M	SXWMPC24AM10001
MP-C-36A-M	SXWMPC36AM10001
DIN-rail end clip, 25 pieces	SXWDINEND10001

## Specifications

<b>AC input</b> <b>Nominal voltage</b> 24 VAC $\sim$ 50/60 Hz <b>Power consumption</b> MP-C-24A-M: 10 VA; -36A-M: 12 VA	<b>Operation environment</b> <b>Ambient temperature, operating</b> 0 to 50 °C (32 to 122 °F) at normal operation <b>Humidity</b> Maximum 95 % RH non-condensing	<b>Voltage output rating</b> 0 to 10 VDC $\equiv$ , 5 kohm (min.) <b>Channels</b> MP-C-24A-M: 20; -36A-M: 28 DO – Relay outputs <b>Relay contact rating</b> 250 VAC $\sim$ / 30 VDC $\equiv$ , 2 A Pilot Duty (C300) <b>Channels</b> MP-C-24A-M: 4; -36A-M: 8
<b>DC input</b> <b>Nominal voltage</b> 24 to 30 VDC $\equiv$ <b>Power consumption</b> MP-C-24A-M: 5 W; -36A-M: 6 W	<b>Mechanical</b> <b>Ingress protection rating</b> IP 20 <b>Plastic flame rating</b> UL94-5VB	
<b>Port types</b> <b>RS-485 port</b> RS-485 (3-pole screw terminal block)	Ub – Universal I/O <b>Input rating</b> 24 VDC $\equiv$ , 2.4 mA	

## Addendum - California Proposition 65 Warning Statement for California Residents

**⚠ WARNING:** This product can expose you to chemicals including lead which is known to the State of California to cause cancer and which is known to the State of California to cause birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

部件名称 (Part Name)	有害物质 (Hazardous Substances)					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr (VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
塑料部件 (Plastic Parts)	○	○	○	○	○	○
电子件 (Electronics)	X	○	○	○	○	○

本表格依据 SJ/T11364 的规定编制。(This table is made according to SJ/T 11364.)

○: 表示该有害物质在该部件所有均质材料中的含量均在 GB/T 26572 规定的限量要求以下。  
 (Indicates that the concentration of hazardous substance in all of the homogeneous materials for this part is below the limit as stipulated in GB/T 26572.)

X: 表示该有害物质至少在该部件的某一均质材料中的含量超出 GB/T 26572 规定的限量要求。  
 (Indicates that the concentration of hazardous substance in at least one of the homogeneous materials used for this part is above the limit as stipulated in GB/T 26572.)

